XL-DAB20NH

- **iPod compatible Micro Stereo System with DAB+ Tuner**
- **USB-Playback and AUX- input (rear)**
- **50 Watt total RMS Output Power**
- **Infrared Remote Control**
- **CD and CD-MP3/WMA playback**
- **DAB+/ FM -/ AM-Tuner with 40 presets**
- **2-Way Speaker Boxes**
- **6-Mode Equalizer Presets, XBASS sound function**

One for all! Sharp's latest DAB+ High Power Micro System with great sound quality, ready for iPod and portable player with USB-Host. The AUX-Input, CD-MP3/-WMA playback, DAB+ and FM/AM RDS-tuner provide a wide range of applications! "Feel" your music supplied by one of 6 preset equalizer sound setings, while the Xbass power for an enhanced bass is send to the 2-Way speaker system!

Amplifier Section
- Peak music power output (total): **- W**
- Music power output (DIN 45 324): **50 W (25+25)W**
- RMS power DIN 45 324: **50 W (25+25)W**
- RMS power DIN 45 500: **30 W (15+15)W**
- Preprogrammed equalizer: ✔
- X-Bass: ✔

Clock/Timer
- Clock/Sleep: ✘/✔
- Timer(Rec/playback): ✘/✔

Input Terminals
- AUX analogue/ USB: ✔/✔

Speaker Systems
- Type: **2-Way System**
- Woofer / Tweeter / Full Range: ✔/✔/✘
- Radiator (Passive cone): **10 cm**
- Dimensions (W x H x D), mm: **132x260x171,5**
- Weight speaker systems (each): **1,98 Kg**

General Section
- Special Features: **Video Out (TV-Out-) terminal for iPOD**
- Operation: **Remote Control, front cabinet**
- Power requirement (AC): **230V/50Hz**
- Dimensions main unit (W x H x D), mm: **155x178x243**
- Weight (main unit): **2,12 Kg**
- Colour Main Unit / Speakers / RC: **Piano black/black/black**
- Stand-by power consumption: **0,6 Watt**
- EAN: **4974019688725**

FM/AM- Tuner Section
- RDS / Preset station memories: **Yes/40 (FM/AM), DAB+ (99 presets)**

CD Player Section
- CD changer: **1 CD-Front Open**
- CD-R/CD-RW*/MP3 playable: ✔/✔/✔
- MP3- / WMA-Navigation: ✔
- Random play/Repeat/Title memories: ✔/✔/✔

Output Terminals
- Speakers/Headphone (3.5 mm): ✔/✔

Accessories
- Remote control with batteries: ✔
- FM indoor-/ AM loop- antenna: ✔/✔